


Pure Sine Wave Inverter

Model :SSN300W-12



pure Sine Wave



Feature:

- ✧ Input Voltage:12V DC
- ✧ Output Voltage:110V,220V,230V,240V
- ✧ Rated Power:300W
- ✧ Surge Power:600W
- ✧ Quality Warranty:1.5 years
- ✧ CE,RoHS, Approved

1. Soft start: Smooth start-up of appliances
2. Universal Protection Circuit: Over-voltage, thermal protection, earth fault protection, overload protection, short circuit protection, bat. Polarity reverse protection, low voltage protection
3. High surge and efficient
4. Low interference Technology
5. USB output: 5V500mA(note: As charger function only)
6. Do not use the USB charger for your appliances when the low battery voltage happen!
7. With power ON/OFF switch and 2 LED indicator: Power, Fault
8. The surge power twice as rated power
- 9.100% pure sine wave output, better than public power (THD<3%)
10. Thermal Methods: Dual cooling fans, temp. Control or 30% load auto. On


Protection Features

1. Overload and over-temperature shut down AC back feed
2. Output short circuit
3. Over-voltage protection
4. Low-voltage alarm and cut-out
5. Earth Leakage Protection
6. Auto. Recover After All Protection

Specification:

Model No	SSN300W-12
Max. Continuous Power	300 watts
Peak Power	600 watts
AC output voltage	110V,120V,220V ,230V, 240V AC
AC output frequency	50 or 60 +/-2 Hz
AC output waveform	Pure Sine Wave
DC input voltage	12VDC
voltage range	10.5~15.0VDC
No Load Current Draw	<0.4 amps
LED Indicator	Input voltage level, output load level and status
Efficiency (Typ.)	>88%
Fuse (12V)	35A *1 (12V)
Bat. Low Alarm	10.5V DC
Bat. Low Shutdown	10.0V DC
Over Load	Shut off output voltage, re-power on to recover
Over Voltag	15.5VDC
Cooling	Loading controlled cooling fan
Dimensions	130×150×53mm(L×W×H)
Weight	1.5Kgs


AC Output Optional:




A
USA



B
AUSTRALIA



C
UNIVERSAL Europe+USA+Japan



D



E
U.K



F
FRANCE



G
GERMANY

Packing Including:

- 1) 300W Pure Sine Wave Inverter
- 2) Connect Cable(Black and Red)
- 3) User Manual