

# Pure Sine Wave Inverter


Model :SSN600W-24



CE   
RoHS  
**1.5** YEAR  
LIMITED  
WARRANTY

## Feature:

- ◇ Input Voltage:24V DC
- ◇ Output Voltage:110V,220V,230V,240V
- ◇ Rated Power:600W
- ◇ Surge Power:1200W
- ◇ Quality Warranty:1.5 years
- ◇ CE,RoHS, Approved



pure Sine Wave

1. Soft start: Smooth start-up of appliances
2. Universal Protection Circuit: Over-voltage, thermal protection, earth fault protection, overload protection, short circuit protection, bat. Polarity reverse protection, low voltage protection
3. High surge and efficient
4. Low interference Technology
5. USB output: 5V500mA(note: As charger function only)
6. Do not use the USB charger for your appliances when the low battery voltage happen!
7. With power ON/OFF switch and 2 LED indicator: Power, Fault
8. The surge power twice as rated power
9. 100% pure sine wave output, better than public power (THD<3%)
10. Thermal Methods: Dual cooling fans, temp. Control or 30% load auto. On


## Protection Features

1. Overload and over-temperature shut down AC back feed
2. Output short circuit
3. Over-voltage protection
4. Low-voltage alarm and cut-out
5. Earth Leakage Protection
6. Auto. Recover After All Protection

## Specification:

Model No	SSN600W-24
Max. Continuous Power	600 watts
Peak Power	1200 watts
AC output voltage	110V,120V,220V or 230V,240V AC
AC output frequency	50 or 60 +/-2 Hz
AC output waveform	Pure Sine Wave
DC input voltage	24VDC
voltage range	21.0~30.0V DC
No Load Current Draw	<0.4 amps
LED Indicator	Input voltage level, output load level and status
Efficiency (Typ.)	>87%
Fuse (12V)	30A *2 (12V)
Bat. Low Alarm	21.0VDC
Bat. Low Shutdown	20.0VDC
Over Load	Shut off output voltage, re-power on to recover
Over Voltage	31.0VDC
Cooling	Loading controlled cooling fan
Dimensions	200×150×70mm(L×W×H)
Weight	2.1Kgs

## AC Output Optional:




A  
USA




B  
AUSTRALIA



C  
UNIVERSAL Europe+USA+Japan



D



E  
U.K



F  
FRANCE



G  
GERMANY

## Packing Including:

- 1) 600W Pure Sine Wave Inverter
- 2) Connect Cable( Black and Red)
- 3) User Manual